

supplementary

Honda CBR 600 2001-2005



1) Ignition coils

Disconnect 6way balck connector on ignition coil wiring harness.
Insert QS wiring harness - see picture below

Check if:

RED wire from QS goes to Black/White to motorcycle.

YELLOW wire from QS goes to Black/White to ignition coil.

2) Ground connection

Connect black wire of QS wiring harness to negative terminal of battery (or to frame of motorcycle)

3) QS sensor

Connect QS sensor to QS wiring harness - black 2 pin connector.

