

# supplementary

## Suzuki GSX-R 1100 to 1998



### 1) Ignition coils

Disconnect Orange/White wire from ignition coil 1.

Connect Yellow wire from QS unit to ignition coil terminal and Red wire from QS unit to Orange/White wire - see picture below.

Do it same with Orange/White wire on ignition coil 2.

### 2) RPM connection

Connect Blue wire from QS unit to ignition coil #1-to W wire. Or to ignition coil #2-to B/Y. Blue wire from QS have to be connected with W (or B/Y) and ignition coil terminal together.

### 3) Ground connection

Connect black wire of QS to negative terminal of battery (or to frame of motorcycle)

### 4) QS sensor

Connect QS sensor to QS wiring harness - black 2 pin connector.

